

KombiSIGN 40 / DesignLOOK

TwinLIGHT Design 24VAC/DC YE







| MECHANICAL DATA | |
|-----------------------------|---------------|
| Height | 59 mm |
| Diameter | 40 mm |
| Materials | PC |
| Dome colour | Clear |
| Protection category | IP66 IP69K |
| Working temperature minimum | -30°C |
| Working temperature maximum | +60°C |
| Weight with packaging | 40 g |
| Product weight | 29 g |

| ELECTRICAL DATA | |
|-----------------------------|--------------------|
| Operating voltage | 24V |
| Operating voltage type | AC/DC |
| Operating voltage frequency | 50Hz |
| Operating voltage tolerance | +/- 10% |
| Rated operational voltage | 24 VDC |
| Rated operational current | 30 mA |
| Rated inrush current | 500 mA |
| Protection class | Protection class 3 |
| Pollution degree | 3 |
| Request to external PSU | SELV/PELV |

| OPTICAL DATA | |
|----------------------|---------------------------------|
| Light source | LED |
| Light colour | Yellow |
| Optical signal image | Blink Permanent TwinLight |
| Blink frequency | 1 Hz |
| Service life optical | 50,000 h maximum |

| APPROVAL DATA | |
|------------------------------|---------|
| Conforms with CE | Yes |
| Conforms with RoHS directive | Yes |
| WEEE | Yes |
| Conforms with ATEX-directive | No |
| Conforms with CCC | No |
| Conforms with UL | cULus |
| UL Type Rating | Type 12 |

For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.



KombiSIGN 40 / DesignLOOK

TwinLIGHT Design 24VAC/DC YE

| Conforms with FCC | No |
|-------------------------------|-----------------------|
| Conforms with IC | No |
| EAC certificate available | Yes |
| Conforms with UKCA (Importer) | Yes (WERMA (UK) Ltd.) |
| Conforms with CMIM | No |
| Conforms with AS-I | No |
| ICAO Certification | No |
| Conforms with DNV | No |
| Conforms with RoHS CN | No |
| Conforms with VdS | No |
| MTTF-value [years] | 1699 |

SC OS Ø40

For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.